

## Relay socket - PR1-BSC2/2X21 - 2833518

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)



Relay socket PR1..., for miniature power relay or miniature switching relay with 1 or 2 PDT or solid-state relay of same construction, 2/2 level design, screw connections, connection facility for input/interference suppression modules

### Product Features

- ✓ Relay base family that can be fitted with 1 PDT or 2 PDT relays or solid-state relays
- ✓ Relay retaining bracket with labeling field and ejection function
- ✓ Plug-in input/interference suppression modules



### Key commercial data

Packing unit	1 pc
Minimum order quantity	10 pc
Weight per Piece (excluding packing)	41.2 GRM
Custom tariff number	85366990
Country of origin	China

### Technical data

#### Dimensions

Width	16 mm
Height	75 mm
Depth with retaining bracket	63 mm (EL1-P16)

#### Ambient conditions

Ambient temperature (operation)	-25 °C ... 85 °C
Ambient temperature (storage/transport)	-25 °C ... 85 °C

#### Connection data

Conductor cross section solid min.	0.2 mm <sup>2</sup>
------------------------------------	---------------------

# Relay socket - PR1-BSC2/2X21 - 2833518

## Technical data

### Connection data

Conductor cross section solid max.	2.5 mm <sup>2</sup>
Conductor cross section stranded min.	0.2 mm <sup>2</sup>
Conductor cross section stranded max.	2.5 mm <sup>2</sup>
Conductor cross section AWG/kcmil min.	26
Conductor cross section AWG/kcmil max	14
2 conductors with same cross section, solid max.	2.50 mm <sup>2</sup>
2 conductors with same cross section, stranded max.	2.50 mm <sup>2</sup>
2 conductors with same cross section, AWG max.	14
Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3

### General

Nominal voltage U <sub>N</sub>	300 V AC/DC
Nominal current I <sub>N</sub>	12 A
Color	green

## Classifications

### eCl@ss

eCl@ss 4.0	27371102
eCl@ss 4.1	27371102
eCl@ss 5.0	27371603
eCl@ss 5.1	27371603
eCl@ss 6.0	27371603
eCl@ss 7.0	27371603
eCl@ss 8.0	27371603

### ETIM

ETIM 2.0	EC001456
ETIM 3.0	EC001456
ETIM 4.0	EC001456
ETIM 5.0	EC001456

### UNSPSC

UNSPSC 6.01	30211917
UNSPSC 7.0901	39121516
UNSPSC 11	39121516

# Relay socket - PR1-BSC2/2X21 - 2833518

## Classifications

### UNSPSC

UNSPSC 12.01	39121516
UNSPSC 13.2	39121516

## Approvals

### Approvals

---

#### Approvals

UL Recognized / cUL Recognized / CSA / cULus Recognized

---


#### Ex Approvals


---

#### Approvals submitted

---

## Approval details

UL Recognized 

cUL Recognized 

CSA 

cULus Recognized 

## Accessories

### Accessories

Bridge

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories


Wire bridge - DB 50- 90 BU - 2821180

Wire bridge, Color: blue



Wire bridge - DB 50- 90 BK - 2820916

Wire bridge, Color: black



Wire bridge - DB 50- 90 GY - 2820929

Wire bridge, Color: gray



### Device marking

Label - EML (15X6) R YE - 0819288



Label, Roll, yellow, unlabeled, can be labeled with: THERMOMARK ROLL, THERMOMARK X, THERMOMARK S1.1,  
Mounting type: Adhesive, Lettering field: 15 x 6 mm

---

### Marking material

Marker labels - MP 1 - 2833631



Equipment marker, labeling surface 6 x 15 mm

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

---

#### Plug-in module

Plug-in module - LDP- 12- 24DC - 2833657



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: A1+, A2-, input voltage: 12 -24 V DC  $\pm$  20%

---

Plug-in module - LDP- 48- 60DC - 2833660



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: A1+, A2-, input voltage: 48 -60 V DC  $\pm$  20%

---

Plug-in module - LDP-110DC - 2833673



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: A1+, A2-, input voltage: 110 V DC  $\pm$  20%

---

Plug-in module - LDM- 12- 24DC - 2833686



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: A1-, A2+ (Japan standard), input voltage: 12 -24 V DC  $\pm$  20%

---

Plug-in module - LDM- 48- 60DC - 2833699



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: A1-, A2+ (Japan standard), input voltage: 48 -60 V DC  $\pm$  20%

---

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Plug-in module - LDM-110DC - 2833709



Plug-in module, for mounting on PR1 and PR2, with damping diode and yellow LED, polarity: A1-, A2+ (Japan standard), input voltage: 110 V DC  $\pm$  20%

---

Plug-in module - LV- 12- 24UC - 2833712



Plug-in module, for mounting on PR1 and PR2, with varistor and yellow LED, input voltage: 12 - 24 V AC/DC  $\pm$  20%

---

Plug-in module - LV- 48- 60UC - 2833725



Plug-in module, for mounting on PR1 and PR2, with varistor and yellow LED, input voltage: 48-60 V AC/DC  $\pm$  20%

---

Plug-in module - LV-120-230AC/110DC - 2833738



Plug-in module, for mounting on PR1 and PR2, with varistor and yellow LED, input voltage: 120 - 230 V AC/110 V DC  $\pm$  20%

---

Plug-in module - V- 12- 24UC - 2833864



Plug-in module, for mounting on PR1 and PR2, with varistor, input voltage: 12-24 V AC/DC  $\pm$  20%

---

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Plug-in module - V- 48- 60UC - 2833877



Plug-in module, for mounting on PR1 and PR2, with varistor, input voltage: 48-60 V AC/DC  $\pm$  20%

---

Plug-in module - V-120-230UC - 2833880



Plug-in module, for mounting on PR1 and PR2, with varistor, input voltage: 120-230 V AC/DC  $\pm$  20%

---

Plug-in module - RC- 12- 24UC - 2833741



Plug-in module, for mounting on PR1 and PR2, with RC element, input voltage: 12 - 24 V AC/DC  $\pm$  20%

---

Plug-in module - RC- 48- 60UC - 2833754



Plug-in module, for mounting on PR1 and PR2, with RC element, input voltage: 48-60 V AC/DC  $\pm$  20%

---

Plug-in module - RC-120-230UC - 2833767



Plug-in module, for mounting on PR1 and PR2, with RC element, input voltage: 120 - 230 V AC/DC  $\pm$  20%

---

### Retaining bracket

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Relay retaining bracket - EL1-P16 - 2833547



Relay retaining bracket, with eject function and integrated equipment marking area (7.5 x 15 mm), to suit relay socket PR1, for 16 mm high miniature power relay and solid-state relay

---

Relay retaining bracket - EL1-P25 - 2833550



Relay retaining bracket, with eject function and integrated equipment marking area (7.5 x 15 mm), to suit relay socket PR1, for 25 mm high miniature switching relay and solid-state relay

---

### Required add-on products

Single relay - REL-MR- 12DC/21HC - 2961309



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, input voltage 12 V DC

---

Single relay - REL-MR- 24DC/21HC - 2961312



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, input voltage 24 V DC

---

Single relay - REL-MR- 48DC/21HC - 2834821



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, input voltage 48 V DC

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Single relay - REL-MR- 60DC/21HC - 2961325



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, 60 V DC

---

Single relay - REL-MR-110DC/21HC - 2961338



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, input voltage 110 V DC

---

Single relay - REL-MR- 24AC/21HC - 2961406



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, input voltage 24 V AC

---

Single relay - REL-MR-120AC/21HC - 2961419



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, input voltage 120 V AC

---

Single relay - REL-MR-230AC/21HC - 2961422



Plug-in miniature power relay, with power contact for high continuous currents, 1 PDT, input voltage 230 V AC

---

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Single relay - REL-MR- 12DC/21HC AU - 2961532



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 PDT, input voltage 12 V DC

---

Single relay - REL-MR- 24DC/21HC AU - 2961545



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 PDT, input voltage 24 V DC

---

Single relay - REL-MR-110DC/21HC AU - 2961561



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 PDT, input voltage 110 V DC

---

Single relay - REL-MR- 24AC/21HC AU - 2961503



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 PDT, input voltage 24 V AC

---

Single relay - REL-MR-120AC/21HC AU - 2961516



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 PDT, input voltage 120 V AC

---

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Single relay - REL-MR-230AC/21HC AU - 2961529



Plug-in miniature power relay, with multi-layer gold contact for high continuous currents, 1 PDT, input voltage 230 V AC

---

Single relay - REL-MR- 12DC/21-21 - 2961257



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 12 V DC

---

Single relay - REL-MR- 24DC/21-21 - 2961192



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 24 V DC

---

Single relay - REL-MR- 48DC/21-21 - 2834834



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 48 V DC

---

Single relay - REL-MR- 60DC/21-21 - 2961273



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 60 V DC

---

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Single relay - REL-MR-110DC/21-21 - 2961202



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 110 V DC

---

Single relay - REL-MR- 24AC/21-21 - 2961435



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 24 V AC

---

Single relay - REL-MR-120AC/21-21 - 2961448



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 120 V AC

---

Single relay - REL-MR-230AC/21-21 - 2961451



Plug-in miniature power relay, with power contact, 2 PDTs, input voltage 230 V AC

---

Single relay - REL-MR- 12DC/21-21AU - 2961299



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 12 V DC

---

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Single relay - REL-MR- 24DC/21-21AU - 2961215



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 24 V DC

---

Single relay - REL-MR- 48DC/21-21AU - 2834847



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 48 V DC

---

Single relay - REL-MR- 60DC/21-21AU - 2961286



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 60 V DC

---

Single relay - REL-MR-110DC/21-21AU - 2961228



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 110 V DC

---

Single relay - REL-MR- 24AC/21-21AU - 2961464



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 24 V AC

---

## Relay socket - PR1-BSC2/2X21 - 2833518

### Accessories

Single relay - REL-MR-120AC/21-21AU - 2961477



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 120 V AC

---

Single relay - REL-MR-230AC/21-21AU - 2961480



Plug-in miniature power relay, with multi-layer gold contact, 2 PDTs, input voltage 230 V AC

---

Single relay - REL-MR- 24DC/1IC - 2961341



Plug-in miniature power relay, with power contact for high switch-on currents, 1 N/O contact, input voltage 24 V DC

---

---