

EVALSPEAR310 - evaluation board for the SPEAr310

1 Description


This user manual describes how to use the EVALSPEAR310 evaluation board for SPEAr310.

It is intended to be used for three main purposes:

- To allow you to quickly evaluate and debug software for the SPEAr310
- Act as a learning tool to rapidly get familiar with the SPEAr310 features
- Provide a starting point for the development of the final application board

The EVALSPEAR310 board is equipped with one MII Ethernet port, four SMII Ethernet ports, six RS232 ports, two HDLC based RS485 ports and one E1/TDM port. Memory devices included are NAND Flash, parallel NOR Flash, serial NOR Flash, and I²C EEPROM.

Figure 1. EVALSPEAR310 evaluation board



Contents

1	Description	1
2	Contents of the kit	6
3	Connectors locations	7
4	Features and block diagram	8
4.1	Features	8
4.2	Block diagram	9
5	Start up	10
5.1	Unpacking	10
5.2	Connection	10
5.3	Bootng procedure	10
6	Block descriptions	11
6.1	MII Ethernet	11
6.2	SMII Ethernet	11
6.3	USB	15
6.4	RS232	15
6.5	HDLC-RS485	16
6.6	HDLC-E1/TDM	18
6.7	General purpose ADC connector	20
6.8	NOR Flash	20
6.9	NAND Flash	21
6.10	Serial NOR Flash	21
6.11	Parallel NOR Flash	21
6.12	EEPROM	21
6.13	DDR2 SDRAM	21
6.14	CPLD	22
6.15	LEDs	22
6.16	Reset button	22

6.17	Debug Interface	22
6.18	Power supply	22
6.19	Jumper settings	23
7	Connectors	25
7.1	MPU JTAG connector	25
7.2	CPLD JTAG connector	25
7.3	TDM master connector J5	25
7.4	TDM slave connector J6	26
7.5	Ethernet RJ45 connectors J15, J18, J19, J21, U25	26
7.6	General purpose ADC connector J27	27
7.7	General purpose GPIO connector J25	28
7.8	RS485 DB9 socket P1, P8	28
7.9	RS232/UART0 DB9 plug connector P2	29
7.10	RS232/UART1 DB9 plug connector P3	29
7.11	RS232/UART2,3,4,5 connector P4,P5,P6,P7	30
7.12	BNC plug connector J2	30
7.13	BNC plug connector J4	30
8	Evaluation board bill of materials (BOM)	31
	Appendix A Licence agreements	42
	Revision history	47

List of tables

Table 1.	MII address of the MII Ethernet PHY at U24	11
Table 2.	Default configuration of the Ethernet PHY in U24	11
Table 3.	SMII addresses of the SMII Ethernet PHYs	12
Table 4.	SMII-1 PHY jumpers	12
Table 5.	SMII-2 PHY jumpers	13
Table 6.	SMII-3 PHY jumper	13
Table 7.	SMII-4 PHY jumper default settings	14
Table 8.	Default configuration of the Ethernet PHYs U18, U19, U20 and U21	15
Table 9.	HDLC-RS485-1 on-board clock jumpers	16
Table 10.	HDLC-RS485-2 on-board clock jumpers	17
Table 11.	HDLC-RS485-1 external clock jumper settings	17
Table 12.	HDLC-RS485-2 external clock jumper settings	18
Table 13.	HDLC-TDM master on-board clock settings	19
Table 14.	HDLC-TDM slave external clock and sync settings	19
Table 15.	General ADC reference voltage settings	20
Table 16.	Memory space map jumpers of NOR Flash	20
Table 17.	SW3 (SoC functional configuration)	23
Table 18.	SW3 (debug configuration)	23
Table 19.	SW3 (functional configuration)	23
Table 20.	SW2 strapping options	23
Table 21.	MPU JTAG connector pin assignment	25
Table 22.	CPLD connector pin assignment	25
Table 23.	TDM master connector J5 pin assignments	26
Table 24.	TDM slave connector J6 pin assignments	26
Table 25.	RJ45 connectors J15, J18, J19, J21, U25	27
Table 26.	General purpose ADC connector J27	27
Table 27.	General purpose GPIO J25	28
Table 28.	RS485 DB9 socket connector P1, P8	28
Table 29.	RS232/UART0 DB9 plug connector P2	29
Table 30.	RS232/UART1 DB9 plug connector P3	29
Table 31.	RS232/UART2, 3, 4, 5 connector P4, P5, P6, P7	30
Table 32.	SPEAr310 bill of materials (BOM)	31
Table 33.	Document revision history	47

List of figures

Figure 1.	EVALSPEAR310 evaluation board	1
Figure 2.	Connectors locations	7
Figure 3.	Block diagram	9
Figure 4.	MPU JTAG connector	25
Figure 5.	CPLD JTAG connector	25
Figure 6.	TDM master connector J5	26
Figure 7.	TDM slave connector J6	26
Figure 8.	Ethernet RJ45 connectors J15, J18, J19, J21, U25 - front view	27
Figure 9.	General purpose ADC connector J27	27
Figure 10.	General purpose GPIO J25	28
Figure 11.	RS485 DB9 socket connector P1, P8	28
Figure 12.	RS232/UART0 DB9 plug connector P2	29
Figure 13.	RS232/UART1 DB9 plug connector P3	29
Figure 14.	RS232/UART2,3,4,5 connector P4,P5,P6,P7	30


2 Contents of the kit

The EVALSPEAR310 evaluation board kit contains:

- SPEAr310 evaluation board
- AC adapter (output voltage 5 V)
- 2 plug adapters (USA/Europe)
- User manual

3 Connectors locations

Figure 2. Connectors locations




4 Features and block diagram

4.1 Features

- SPEAr310 embedded MPU
- Up to 2 Gbits DDR2 333 MHz (std 128 Mbytes)
- Up to 1.5 Gbytes Parallel NOR Flash (std 16 Mbytes)
- Up to 16 Mbytes Serial NOR Flash memory (std 64 Mbytes)
- Up to 2 Gbits NAND Flash memory (std 64 Mbytes)
- 4 Kb Serial I²C EEPROM
- 4 Mb SPI Flash memory
- Two USB 2.0 full Host port channels
- One USB 2.0 high speed Device
- One 10/100 Ethernet port based on MII PHY
- Four 10/100 Ethernet port based on SMII PHY
- One E1, 2x BNC/RJ48(2.048 Mbits)
- Two HDLC RS485 DB9 ports (up to 4 MHz)
- One HDLC-TDM port (8 Mb, 128 TS)
- Six Serial ports (up to 115 kbaud)
- 8 ADC channels (10 bit, 1 Msamples)
- 6 GPIOs
- JTAG debug port

4.2 Block diagram

Figure 3. Block diagram



5 Start up

5.1 Unpacking

ELECTROSTATIC WARNING:

The SPEAr310 evaluation board is shipped in protective anti-static packaging. The board must not be subjected to high electrostatic potentials. General practices for working with static sensitive devices should be applied when working with this board.

- **Wear an anti-static wristband** - Wearing a simple anti-static wristband can help to prevent ESD from damaging the SPEAr310 evaluation board.
- **Self-grounding** - Touch a grounded conducting material before handling and periodically while handling the SPEAr310 evaluation board.
- **Use an anti-static pad** - When configuring the SPEAr310 evaluation board, place it on an anti-static pad to reduce the possibility of ESD damage.
- **Only handle the board edges** - When handling the SPEAr310 evaluation board.

5.2 Connection

- Connect a serial cable (RS232 on UART0) to a host PC.
- On a host PC running Windows or Linux, start the Terminal program.
- Connect the AC Adapter to a power outlet.
- Power ON the board (plug the jack of the AC/Adapter on VB1). A sequence of boot messages is displayed, followed by the Linux console prompt.

For more information, refer to the *Getting started with Linux for SPEAr (UM0844)* available on www.st.com.

5.3 Booting procedure

The SPEAr310 board is able to boot a Linux kernel pre-installed in the serial NOR Flash.

At power on, the serial port outputs a brief header message with some uBoot information (uBoot version, SDK version, and some internal hardware information). At this point you can choose to:

1. **Stop the system directly in uBoot:** For this you have to press the spacebar on the host computer keyboard before the boot delay time expires (default is 3 seconds).
2. **Boot Linux:** The system logs you in automatically as super user and the Linux shell prompt is displayed on the screen.

6 Block descriptions

6.1 MII Ethernet

There is one MII Ethernet PHY available on the board at U24, connected through the media independent interface to the Ethernet MAC on the CPU processor.

By default the MII address of the MII Ethernet PHY is selected as shown in [Table 1](#).

Table 1. MII address of the MII Ethernet PHY at U24

Component	MII address
U24	0x04

By default the initial configuration of the MII Ethernet PHY is selected as shown in [Table 2](#).

Table 2. Default configuration of the Ethernet PHY in U24

Function	Default configuration
Auto negotiation	Enabled
10/100 Mbps	100 Mbps selected for auto negotiation advertisement
Half/Full duplex	Full duplex selected for auto negotiation advertisement
Internal loopback	Disabled
Power down	Disabled (PHY active)
MII/RMII mode	MII selected

There are two LEDs embedded in each RJ45 connector (U25) which are used to indicate the status of the line:

- The green LED in the connector is driven on continuously when the Ethernet link is established with the counterpart.
- The yellow LED in the connector blinks when there is TX or RX activity.

The Serial Management Interface (SMI) is part of the MII interface and is used to transfer management information between MAC and PHY (access to the PHY registers).

For the correct functionality of the MII Ethernet PHY (U24 in MII mode), it is necessary to clock with a by 25 MHz clock. The default option is to use oscillator OSC1.

6.2 SMII Ethernet

There are four SMII Ethernet PHYs available on the board at U18, U19, U20 and U21, connected through serial media independent interfaces to the Ethernet MACs in the SPEAr310 MPU.

By default the SMII addresses of the SMII Ethernet PHYs are selected as shown in [Table 3](#).

Table 3. SMII addresses of the SMII Ethernet PHYs

Component	MII address
U18	0x01
U19	0x03
U20	0x05
U21	0x07

By default the external configuration of the SMII-1 Ethernet PHYs is selected as shown in [Table 4](#).

Table 4. SMII-1 PHY jumpers

Jumper	Description	Default configuration
JP13, JP14, JP15	SMII PHY U18 mode configuration: Default: JP13-open, JP14-fitted, JP15-open: Set U18 to work as SMII function	 ● ● JP10  ● ● JP11  ● ● JP12
JP10, JP11, JP12	SMII PHY U18 address configurations: Default: JP10-open, JP11-open, JP12-open: Set SMII-1 PHY address: 0x01	 ● ● JP10  ● ● JP11  ● ● JP12
JP16	Isolate mode: Pull-up = Enable Pull-down (default) = Disable	 ● ● JP16
JP17	Nway auto-negotiation enable: Pull-up (default) = Enable auto-negotiation Pull-down = Disable auto-negotiation	 ● ● JP17
JP18	Speed mode: Pull-up (default) = 100 Mbps Pull-down = 10 Mbps	 ● ● JP18
JP19	Duplex mode: Pull-up (default) = Half duplex Pull-down = Full duplex	 ● ● JP19

By default the external configuration of the SMII-2 Ethernet PHYs is selected as shown in [Table 5](#).

Table 5. SMII-2 PHY jumpers

Jumper	Description	Default configuration
JP23, JP24, JP25	SMII PHY U19 mode configuration: Default: JP23-open, JP24-fitted, JP25-open: Set U19 to work as SMII function	● ● JP23 ● ● JP24 ● ● JP25
JP20, JP21, JP22	SMII PHY U19 addresses configuration: Default: JP20-open, JP21-open, JP22-open: Set SMII-2 PHY address: 0x03	● ● JP20 ● ● JP21 ● ● JP22
JP26	ISOLATE mode: Pull-up = Enable Pull-down (default) = Disable	● ● JP26
JP27	Nway auto-negotiation enable: Pull-up (default) = Enable auto-negotiation Pull-down = Disable auto-negotiation	● ● JP27
JP28	Speed mode: Pull-up (default) = 100 Mbps Pull-down = 10 Mbps	● ● JP28
JP29	Duplex mode: Pull-up (default) = Half duplex Pull-down = Full duplex	● ● JP29

By default the external configuration of the SMII-3 Ethernet PHYs is selected as shown in [Table 6](#).

Table 6. SMII-3 PHY jumper

Jumper	Description	Default configuration
JP33, JP34, JP35	SMII PHY U20 mode configuration: Default: JP33-open, JP34-fitted, JP35-open: Set U20 to work as SMII function	● ● JP33 ● ● JP34 ● ● JP35
JP30, JP31, JP32	SMII PHY U20 addresses configuration: Default: JP30-open, JP31-open, JP32-open: Set SMII-3 PHY address: 0x05	● ● JP30 ● ● JP31 ● ● JP32
JP36	ISOLATE mode: Pull-up = Enable Pull-down (default) = Disable	● ● JP36

Table 6. SMII-3 PHY jumper (continued)

Jumper	Description	Default configuration
JP37	Nway auto-negotiation enable: Pull-up (default) = Enable auto-negotiation Pull-down = Disable auto-negotiation	● ● JP37
JP38	Speed mode: Pull-up (default) = 100 Mbps Pull-down = 10 Mbps	● ● JP38
JP39	Duplex mode: Pull-up (default) = Half duplex Pull-down = Full duplex	● ● JP39

By default the external configuration of the SMII-4 Ethernet PHYs is selected as shown in [Table 7](#).

Table 7. SMII-4 PHY jumper default settings

Jumper	Description	Default configuration
JP43, JP44, JP45	SMII PHY U21 mode configuration: Default: JP43-open, JP44-fitted, JP45-open: Set U21 to work as SMII function	● ● JP43 ● ● JP44 ● ● JP45
JP40, JP41, JP42	SMII PHY U21 address configurations: Default: JP40-open, JP41-open, JP42-open: Set SMII-4 PHY address: 0x07	● ● JP40 ● ● JP41 ● ● JP42
JP46	Isolate mode: Pull-up = Enable Pull-down (default) = Disable	● ● JP46
JP47	Nway auto-negotiation enable: Pull-up (default) = Enable auto-negotiation Pull-down = Disable auto-negotiation	● ● JP47
JP48	Speed mode: Pull-up (default) = 100 Mbps Pull-down = 10 Mbps	● ● JP48
JP49	Duplex mode: Pull-up (default) = Half duplex Pull-down = Full duplex	● ● JP49

By default the initial configuration of the MII Ethernet PHYs is selected as shown in [Table 8](#).

Table 8. Default configuration of the Ethernet PHYs U18, U19, U20 and U21

Function	Default configuration
Auto negotiation	Enabled
10/100 Mbits	100 Mbits selected for auto negotiation advertisement
Half/Full duplex	Full duplex selected for auto negotiation advertisement
Internal Loopback	Disabled
Power down	Disabled (PHY active)
MII/SMII mode	SMII selected

There are two LEDs embedded in each RJ45 connector (J15, J18, J19, J21) which are used to indicate the status of the line:

- The red LEDs: D6, D8, D10, D12 in the connector are driven on continuously when the Ethernet link is established with the counterpart.
- The red LEDs: D5, D7, D9, D11 in the connector blinks when there is TX or RX activity.

The Serial Management Interface (SMI) is part of the SMII interface and is used to transfer management information between MAC and PHY (access to the PHY registers). All these four SMII PHYs use same SMI to configure them.

For the SMII Ethernet PHYs (U18,U19,U20,U21 in SMII mode) to function correctly, it is necessary to clock them with a 125 MHz clock. There are two ways to provide a 125 MHz clock to the devices. The default option is to use oscillator U2, the other option is to incorporate the CPU board signal PL_CLK2 (from PLL2) which must be configured in the software. In order to switch from the U2 to PLL1, it is necessary to solder a resistor in R2 (33 Ω) resistor and to remove resistor R8.

6.3 USB

The evaluation board supports two USB Host ports (J30) and one USB slave port (J29) compliant with the USB2.0 Spec. ECHI and OCHI modes are available and supported.

6.4 RS232

There are six UARTs on the board. UART0 and UART1 use DB9 connectors P2 and P3., UART2, UART3, UART4 and UART5 use 3-pin connectors (P4,P5,P6,P7).

UART0 features two modes: using either the full modem control signals or only RX/TX signals

In full modem mode, it uses the U33, U34 RS232 transceivers fully. In this case, use six jumpers to connect the J31 connector: 1<->2, 3<->4,5<->6,7<->8,9<->10,11<->12, so then the UART3, UART4 and UART5 functions are disabled. When it uses only RX/TX signals, it uses only the U34 RS232 transceiver.

UART1 features only RX/TX functionality. It uses the RS232 transceiver at U32.

UART2 features only RX/TX functionality. It uses the RS232 transceiver at U32 and its RS232_2 signals are available on the P4 connector.

UART3 features only RX/TX functionality. It uses the RS232 transceiver at U33 and its RS232_2 signals are available on the P5 connector.

UART4 features only RX/TX functionality. It uses the RS232 transceiver at U33 and its RS232_2 signals are available on the P6 connector.

UART5 features only RX/TX functionality. It uses the RS232 transceiver at U34 and its RS232_2 signals are available on the P7 connector.

Do not install jumpers in J31 when UART3, UART4 and UART5 are enabled and used.

6.5 HDLC-RS485

There are two HDLC-RS485s on the board, they are connected to RS485 transceiver (U16 and U60) and use DB9 connectors (P1 and P8).

HDLC-RS485 features the half-duplex communication, RXD and TXD single-end signals are connected to one RS485 transceiver, by enabling CTS function, it can detect and avoid all the possible bus conflict.

For the correct functionality of the HDLC-RS485, it is necessary to clock them by external clock (TCLK, RCLK), the maxim clock frequency is 3.88MHz, There are two ways to deliver the clocks to CPU. The default option is to use on-board clocks (819.2KHz) that are generated by U38 CPLD.

By default the on-board clock configuration of HDLC-RS485-1 is selected as shown in [Table 9](#).

Table 9. HDLC-RS485-1 on-board clock jumpers

Jumper	Description	Configuration
JP65	Supply on-board clocks or external clocks to CPU for HDLC-RS485-1 TCLK. (Default - fitted) to use on board clocks (PIN-1)	
JP66	Supply on-board clocks or external clocks to CPU for HDLC-RS485-1 RCLK. (Default - fitted) to use on board clocks (PIN-1)	

By default the on-board clock configuration of HDLC-RS485-2 is selected as shown in [Table 10](#).


Table 10. HDLC-RS485-2 on-board clock jumpers

Jumper	Description	Configuration
JP62	Supply on-board clocks or external clocks to CPU for HDLC-RS485-2 TCLK. (Default - fitted) to use on board clocks (PIN-1)	
JP63	Supply on-board clocks or external clocks to CPU for HDLC-RS485-2 RCLK. (Default - fitted) to use on board clocks (PIN-1)	

The other option is to use the external clock signals, it is necessary to remove jumpers on JP65, JP66, JP62, JP63, and then plug the related clock signals cables to connectors: JP65, JP66, JP67, JP62, JP63, JP64.


By default the external clock configuration of HDLC-RS485-1 is selected as shown in [Table 11](#).

Table 11. HDLC-RS485-1 external clock jumper settings

Jumper	Description	Configuration
JP65	Supply on-board clocks or external clocks to CPU for HDLC-RS485-1 TCLK. Setting: to use external clocks (PIN-2)	 TCLK RCLK GND
JP66	Supply on-board clocks or external clocks to CPU for HDLC-RS485-1 RCLK. Setting: to use external clocks (PIN-2)	
JP67	Signal Ground	

By default the external clock configuration of HDLC-RS485-2 is selected as shown in [Table 12](#).

Table 12. HDLC-RS485-2 external clock jumper settings

Jumper	Description	Configuration
JP62	Supply on-board clocks or external clocks to CPU for HDLC-RS485-2 TCLK. Setting: to use external clocks (PIN-2)	 1 2 TCLK RCLK GND
JP63	Supply on-board clocks or external clocks to CPU for HDLC-RS485-2 RCLK. Setting: to use external clocks (PIN-2)	
JP64	Signal Ground	

6.6 HDLC-E1/TDM

There is one HDLC-E1/TDM on the board, it features two modes: HDLC-E1 and HDLC-TDM.

For HDLC-E1 mode, it uses E1 PHY(U6, DS21354) to communicate with other boards or systems, the connectors are J4 (E1-Receiver), J2 (E1-Transmit) and J3 (RJ48 includes TXD/RXD). The software has to read and write to the E1 PHY registers via the EMI bus to initialize, configure and control the E1 PHY.

For HDLC-E1 mode to function properly, it has to be driven by the external clocks (TCLK, RCLK) and external sync (RSYNC,TSYNC). The clock frequency is 2.048 MHz, the sync frequency is 8 kHz. The default setting is to use the on-board clocks and syncs that are generated by the E1 PHY (U36).

For HDLC-TDM mode, no PHY is required and the 128 time slot TDM signals are transmitted to and received from other boards or systems via the J5 connector. For HDLC-TDM mode to function properly, it has to be driven by the external clocks (TCLK, RCLK) and external sync (RSYNC,TSYNC). The clock frequency is 8.192 MHz, the sync frequency is 8 kHz.

There are two ways to deliver the clocks and syncs to the SPEAr. The default option is to use the on-board clocks (8.192 MHz) and syncs (8 kHz) that are generated by the U38 CPLD, in this case, it act as TDM master. At the same time, it can also provide these source clocks and syncs to other TDM slave boards or systems.

By default the on-board clocks and sync configuration of HDLC-TDM is selected as shown in [Table 13](#)

Table 13. HDLC-TDM master on-board clock settings

Jumper	Description	Configuration
JP6	Supply on-board clocks and syncs Default: output TDM_RSINC(JP6-6), TDM_RCLK(JP6-8), TDM_TSYNC(JP6-10) and TDM_TCLK(JP6-12) TDM_RCLK,TDM_TCLK: 8.192MHz TDM_RSINC, TDM_TSYNC: 8 kHz JP5-13 and JP6-13 are ground.	
JP5	Receive clocks and syncs to SPEAr for HDLC-TDM. Default: input TDM_RSINC(JP5-6), TDM_RCLK(JP5-8), TDM_TSYNC(JP5-10) and TDM_TCLK(JP5-12,) Red wire: connect JP6 to JP5 Blue wire: output clocks and syncs to others slave boards	
JP5-2	Input HDLC-TDM RXD to SPEAr, it needs to be connected to the TXD signal of other HDLC-TDM slave boards.	
JP5-4	Output HDLC-TDM TXD from SPEAr to RXD signal of other HDLC-TDM slave boards.	

The other option is to use the external clock and sync signals, in this case, it act as TDM slave, it is necessary to remove connection between JP5 with JP6, and then plug the related external clock and sync signals cables to connectors: JP5.

By default the external clocks and syncs jumpers configuration of HDLC-TDM slave is selected as shown in [Table 14](#)

Table 14. HDLC-TDM slave external clock and sync settings

Jumper	Description	Configuration
JP5	Receive clocks and syncs to CPU for HDLC-TDM from external boards. Default: input TDM_RSINC(JP6-6), TDM_RCLK(JP6-8), TDM_TSYNC(JP6-10) and TDM_TCLK(JP6-12) TDM_RCLK,TDM_TCLK: 8.192MHz TDM_RSINC, TDM_TSYNC: 8KHz JP5-13 is ground. Red wire: input clocks and syncs from other HDLC_TDM slave boards	
JP5-2	Input HDLC-TDM RXD to CPU, it needs to be connected to TXD signal of other HDLC-TDM slave boards.	
JP5-4	Output HDLC-TDM TXD from CPU to RXD signal of other HDLC-TDM slave boards.	

6.7 General purpose ADC connector

Eight analog input lines are available on J27 connector. Inside the connector it is also possible to determine the range of the conversion by setting the conversion limits on the pin J27-19 (lower limit) and J27-1 (upper limit) via jumpers.

By default the on-board VREFP and VREFN jumper configuration of ADC is selected as shown in [Table 15](#).

Table 15. General ADC reference voltage settings

Jumper	Description	Configuration
J27-1	Connects the +2V5_ADC on-board ADC supply voltage to the ADC_VREFP pin of the CPU board (Default)	
J27-2	Connects the external ADC application supply voltage to the ADC_VREFP pin J27-1 of the CPU board	
J27-19	Connects the application board GND of the ADC supply voltage domain to the ADC_VREFN pin of the CPU board (Default)	
J27-20	Connects the external ADC application GND (lower limit) supply voltage to the ADC_VREFN pin J27-19 of the CPU board	

The following relationship between the pins should be guaranteed in the application:

$$\begin{aligned}
 0V &\leq J27-19 \leq J27-3-J27-17 \leq J27-1 \leq +2.5V \\
 GND &\leq ADC_VREFN \leq AIN0-AIN7 \leq ADC_VREFP \leq +2V5ADC
 \end{aligned}$$

6.8 NOR Flash

The NOR Flash is connected to the EMI interface of CPU, two NOR Flash (U7,U10) are available on the board, the bit-width is 32-bit, the current memory size is 128Mbit. The 32bit NOR Flash is mapped to memory space of CPU, use Jumpers (JP1,JP2,JP3,JP4,JP5,JP6) to select one of six memory space.

By default the memory space mapping of NOR Flash is selected as shown in [Table 16](#)

Table 16. Memory space map jumpers of NOR Flash

Jumper	Description	Configuration
JP1	NOR Flash is mapped to EMI CSn0 memory space: 0x50000000	
JP2	Nor Flash is mapped to EMI CSn1 memory space: 0x60000000	

Table 16. Memory space map jumpers of NOR Flash (continued)

Jumper	Description	Configuration
JP3	NOR Flash is mapped to EMI CSn2 memory space: 0x70000000	
JP4	NOR Flash is mapped to EMI CSn3 memory space: 0x80000000	
JP5	NOR Flash is mapped to EMI CSn4 memory space: 0x90000000	
JP6	NOR Flash is mapped to EMI CSn5 memory space:	

6.9 NAND Flash

The NAND Flash is connected to the EMI interface of CPU, one NAND Flash (U4) is available on the board, the bit-width is 8-bit, and the current memory size is 8GMBit.

6.10 Serial NOR Flash

There are two serial NOR Flash, one Serial NOR Flash (U26) is connected to the SMI interface of CPU, the bit-width is 8-bit, and the current memory size is 64Mbit; the another serial NOR FLASH (U29) is connected to the SPI interface of CPU, the bit-width is 8-bit, and the current memory size is 4Mbit.

6.11 Parallel NOR Flash

There are two Parallel NOR FLASH (U7, U10) connected to the EMI interface of CPU, the bit-width is 32-bit, and the current memory size is 128Mbit.

6.12 EEPROM

The EEPROM is connected to the I2C interface of CPU, one EEPROM (U28) is available on the board, the bit-width is 8-bit, and the current memory size is 4Kbit.

6.13 DDR2 SDRAM

The DDR2 SDRAM is connected to the DDR2 interface of CPU, one DDR2 SDRAM (U23) is available on the board, the bit-width is 16-bit, and the current memory size is 1Gbit.

6.14 CPLD

The board includes a XILINX CPLD (U38) that implement E1 PHY initial configuration, HDLC-RS485 on-board clocks generation, HDLC-TDM on-board clocks/syncs generation and timing matching for CPU EMI bus to access E1 PHY internal registers.

J8 is the connector for CPLD JTAG emulator to download programming file.

6.15 LEDs

There are 2 general purpose LEDs (D33,D34) available on the left side of the board. All LEDs are driven on when the related CPLD IO pin is driven high.

GPIO59 (D33), GPIO58 (D34)

6.16 Reset button

A manual reset button (SW1) is available on the board's right side.

6.17 Debug Interface

A debug interface is provided:

The JTAG interface provides "static" debug capability. This means that it is possible to set a breakpoint and, when the system stops, to verify the contents of the memory and/or registers and modify them if needed.

6.18 Power supply

This block, receiving 5V from an external AC/DC regulator will provide all the Voltage needed that are:

- 1.2V (Switching regulator PM6641) to supply the internal logic of SPEAr310
- 1.8V (Switching regulator PM6641) for the DDR2memory
- 2.5V (LDO 1117A regulator) for the analog portion of SPEAr310
- 3.3V (Switching regulator PM6641) to supply the other interfaces

The board is protected against over voltage by U61 (STBP120DVK6F).

A power monitor is also present to provide the general reset for the board.

6.19 Jumper settings

Table 17. SW3 (SoC functional configuration)

Bit	Description
1	Test0 - refer to the table below for the configuration settings
2	Test1 - refer to the table below for the configuration settings
3	Test2 - refer to the table below for the configuration settings
4	Test3 - refer to the table below for the configuration settings
5	Test4 - refer to the table below for the configuration settings
6	BootSel - refer to the table below for the configuration settings

Table 18. SW3 (debug configuration)

Test bit		Description
1	2	
0	0	Normal Mode (No debug enabled)
0	1	ARM1 JTAG connected to J26
1	0	The ARM ETM bus available, but not linked out on this board.

Table 19. SW3 (functional configuration)

Test bit				Description
6	5	4	3	
1	0	1	1	Configuration 3

Bits 3, 4, and 5 allow you to set the Functional configuration. The default configuration is Configuration 3.

Table 20. SW2 strapping options

SW2-x	Description	Settings	
SW2_1	Little/Big endian	0	Little endian (default)
		1	Big endian
SW2_2	EMI_ACK#	0	ACK enabled
		1	GPIO
SW2_3	NAND bus width	0	8-bit NAND Flash
		1	16-bit NAND Flash

Table 20. SW2 strapping options (continued)

SW2-x	Description	Settings			
SW2_4 SW2_5	NOR Flash bus width	SW2_4	SW2_5		
		0	0		8-bit NOR Flash
		0	1		16-bit NOR Flash
		1	0		32-bit NOR Flash
SW2_6 SW2_7 SW2_8	Boot device	SW2_6	SW2_7	SW2_8	
		0	0	0	Serial Flash
		0	0	1	NOR Flash
		0	1	0	NAND Flash
		0	1	1	USB

Note: When DIP switch SW2-X is in the ON position, the bit value is 0. When the DIP switch is in the OFF position, the bit value is 1.

7 Connectors

7.1 MPU JTAG connector

Figure 4. MPU JTAG connector




Table 21. MPU JTAG connector pin assignment

Pin	Signal	Pin	Signal	Pin	Signal	Pin	Signal
1	+3V3	6	GND	11	NC	16	GND
2	+3V3	7	TMS	12	GND	17	NC
3	nTRST	8	GND	13	TDO	18	GND
4	GND	9	TCK	14	GND	19	NC
5	TDI	10	GND	15	NC	20	NC

7.2 CPLD JTAG connector

Figure 5. CPLD JTAG connector




Table 22. CPLD connector pin assignment

Pin	Signal	Pin	Signal	Pin	Signal
1	+3V3	3	TCK	5	TDI
2	+GND	4	TDO	6	TMS

7.3 TDM master connector J5

This connector is the TDM interface for SPEAr310 TDM HDLC controller.

Figure 6. TDM master connector J5




Table 23. TDM master connector J5 pin assignments

Pin	Signal	Pin	Signal	Pin	Signal
1	GND	6	TDM_RSYNC	11	GND
2	TDM_RXD	7	GND	12	TDM_TCLK
3	GND	8	TDM_RCLK	13	GND
4	TDM_TXD	9	GND	14	N.C
5	GND	10	TDM_TSYNC		

7.4 TDM slave connector J6

This connector provides TDM clock and sync signals to master interface.

Figure 7. TDM slave connector J6




Table 24. TDM slave connector J6 pin assignments

Pin	Signal	Pin	Signal	Pin	Signal
1	GND	6	TDM_RSYNC	11	GND
2	N.C	7	GND	12	TDM_TCLK
3	GND	8	TDM_RCLK	13	GND
4	N.C	9	GND	14	N.C
5	GND	10	TDM_TSYNC		

7.5 Ethernet RJ45 connectors J15, J18, J19, J21, U25

J15, J18, J19, J21 is for SMI Ethernet.

U25 is for MII Ethernet.

Figure 8. Ethernet RJ45 connectors J15, J18, J19, J21, U25 - front view




Table 25. RJ45 connectors J15, J18, J19, J21, U25

Pin number	Description	Pin number	Description
1	TxData+	2	TxData-
3	RxData+	4	NC
5	NC	6	RxData-
7	NC	8	NC

7.6 General purpose ADC connector J27

Figure 9. General purpose ADC connector J27




Table 26. General purpose ADC connector J27

Pin	Signal	Pin	Signal	Pin	Signal	Pin	Signal
1	ADC VREF POSITIVE	6	GND	11	AIN4	16	GND
2	+2V5	7	AIN2	12	GND	17	AIN7
3	AIN0	8	GND	13	AIN5	18	GND

Table 26. General purpose ADC connector J27 (continued)

Pin	Signal	Pin	Signal	Pin	Signal	Pin	Signal
4	GND	9	AIN3	14	GND	19	ADC VREF NEGATIVE
5	AIN1	10	GND	15	AIN6	20	GND

7.7 General purpose GPIO connector J25

Figure 10. General purpose GPIO J25




Table 27. General purpose GPIO J25

Pin	Signal	Pin	Signal	Pin	Signal	Pin	Signal
1	+3V3	4	basGPIO2	7	basGPIO5	10	TXD0
2	basGPIO0	5	basGPIO3	8	TXD2	11	TX_CLK
3	basGPIO1	6	basGPIO4	9	TXD1	12	GND

7.8 RS485 DB9 socket P1, P8

Figure 11. RS485 DB9 socket connector P1, P8




Table 28. RS485 DB9 socket connector P1, P8

Pin number	Description	Pin number	Description
1	NC	6	NC
2	NC	7	A
3	NC	8	B
4	NC	9	NC
5	GND		

7.9 RS232/UART0 DB9 plug connector P2

Figure 12. RS232/UART0 DB9 plug connector P2




Table 29. RS232/UART0 DB9 plug connector P2

Pin number	Description	Pin number	Description
1	UART0_DCD	6	UART0_DSR
2	UART0_RX	7	UART0_RTS
3	UART0_TX	8	UART0_CTS
4	UART0_DTR	9	UART0_RI
5	GND		

7.10 RS232/UART1 DB9 plug connector P3

Figure 13. RS232/UART1 DB9 plug connector P3




Table 30. RS232/UART1 DB9 plug connector P3

Pin number	Description	Pin number	Description
1	NC	6	NC
2	UART1_RX	7	NC
3	UART1_TX	8	NC
4	NC	9	NC
5	GND		

7.11 RS232/UART2,3,4,5 connector P4,P5,P6,P7

Figure 14. RS232/UART2,3,4,5 connector P4,P5,P6,P7




Table 31. RS232/UART2, 3, 4, 5 connector P4, P5, P6, P7

Pin number	Description	Pin number	Description
1	TXD	3	GND
2	RXD		

7.12 BNC plug connector J2

This connector is the output stream for E1.

7.13 BNC plug connector J4

This connector is the input stream for E1.

8 Evaluation board bill of materials (BOM)

Table 32. SPEAr310 bill of materials (BOM)

Item	Description	Part number	Manu- facturer	Qty	Reference	Part
1	Capacitor/100 nF/16 V/ 10%/SC0603/X7R			119	C1, C2, C3, C4, C6, C7, C8, C9, C10, C14, C15, C16, C17, C18, C19, C20, C21, C24, C25, C26, C29, C32, C40, C52, C54, C55, C56, C61, C62, C64, C65, C66, C68, C69, C70, C73, C79, C80, C82, C83, C84, C86, C87, C88, C94, C95, C97, C98, C99, C101, C102, C103, C109, C110, C112, C113, C114, C116, C117, C118, C120, C123, C124, C125, C126, C127, C128, C129, C130, C131, C132, C133, C134, C135, C136, C137, C138, C139, C140, C143, C146, C147, C148, C149, C150, C154, C155, C156, C158, C160, C161, C192, C193, C194, C195, C196, C197, C198, C199, C200, C201, C202, C203, C204, C205, C209, C210, C211, C212, C213, C214, C215, C216, C217, C218, C219, C220, C221, C655	0.1uF-0603
2	Capacitor/1 uF/16 V/10 %/SC1206/X7R			1	C5	1uF-1206
3	Capacitor/10 uF/16 V/1 0%/SC1206/X7R	CL31F106ZPA E	SNMSUNG	12	C23, C31, C33, C34, C35, C36, C39, C43, C44, C51, C53, C657	10uF-1206
4	Capacitor/33 nF/16 V/1 0%/SC0603/X7R			1	C27	33nF-0603
5	Capacitor/100 uF/25 V/ 100%/0.9 ohm/NO/STC 7343/Tan/RoHS	TAJD107K025 RNJ	AVX	1	C28	100u-TAJ-R

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
6	Capacitor/22 uF/25 V/2 0%/1.4 ohm/NO/STC60 32/Tan/RoHS	TAJ2226M02 5RNJ	AVX	13	C30, C58, C67, C71, C76, C85, C89, C91, C115, C119, C229, C235, C237	22uF-TAJ-R NO POP
7	Capacitor/470 pF/SC06 03/X7R(X5R, Y5V, C0G)	CL10B471KB NC	SNMSUNG	1	C37	470pF-0603
8	Capacitor/22 nF/10 V/1 0%			3	C38, C41, C42	22nF-0603
9	Capacitor/2.2 nF/NO/N O/SC0603	CL 10B222KBNC	SNMSUNG	1	C45	2.2nF-0603
10	Capacitor/47 uF/10 V/2 0%/1.2 ohm/NO/STC60 32/Tan/	TCSCS1A476 MCAR	SNMSUNG	4	C46, C50, C72, C656	47uF-TAJ-R
11	Capacitor/220 uF/16 V/ 20%/0.5 ohm/NO/STC7 343/Tan/	TAJE227M016 RNJ	AVX	2	C48, C658	220uF-TAJ-R
12	Capacitor/10 uF/25 V/2 0%/NO/NO/STC6032/T an/			25	C57, C75, C90, C100, C104, C105, C106, C206, C207, C208, C222, C224, C225, C226, C228, C230, C231, C232, C233, C234, C236, C238, C239, C240, C241	10uF-TAJ-R
13	Capacitor/1 nF/2 kV/N O/SC1206/NO			10	C59, C60, C77, C78, C92, C93, C107, C108, C244, C245	1000pF-1206
14	Capacitor/100 pF/NO/N O/SC0603/NO	CL10C101JB NC	SNMSUNG	4	C63, C81, C96, C111	100pF-0603
15	Capacitor/22 uF/25 V/2 0%/1.4 ohm/NO/STC60 32/Tan/	TAJ2226M02 5RNJ	AVX	1	C74	22uF-TAJ-R
16	Capacitor/15 pF/50 V/5 %/SC0603/COG			4	C141, C142, C151, C152	15PF-0603
17	Capacitor/10 pF/NO/N O/SC0603/	CL10C100JB NC	SNMSUNG	2	C144, C145	10PF-0603
18	Capacitor/33 pF/NO/N O/SC0603/	CL10C330JB NC	SNMSUNG	2	C153, C157	33PF-0603
19	Capacitor/10 nF/NO/N O/SC0603/X7R(X5R, Y5V, C0G)	CL10B103KB 8NNNC	SNMSUNG	2	C159, C191	0.01uF-0603

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
20	Capacitor/100 nF/10 V/ 10%/SC0402/X5R			24	C162, C163, C164, C165, C166, C167, C168, C169, C170, C171, C172, C173, C174, C175, C176, C177, C178, C179, C180, C181, C182, C183, C184, C185	0.1uF-0603
21	Capacitor/10 uF/25 V/2 0%/NO/NO/STC6032/T an			4	C223, C227, C242, C243	10uF-TAJ-R NO POP
22	LED/GREEN/SLED080 5			15	D1, D21, D22, D23, D24, D25, D26, D27, D28, D29, D30, D31, D32, D33, D34	GREEN
23	LED/RED/SLED0805			14	D5, D6, D7, D8, D9, D10, D11, D12, D13, D14, D15, D17, D19, D20	RED
24	Diode/70V/200 mA/ 250 mW/SOT23/RoHS	BAV70		1	D16	BAV70
25	Diode/600/4 A/ 200 mW/DPAK/RoHS	TS420-600B	ST	1	D35	SCR TS420-B_1
26	Header/single row/short/vertical/2.54 mm pin pitch header	1x2		52	JP1, JP2, JP3, JP4, JP5, JP6, JP10, JP11, JP12, JP13, JP14, JP15, JP16, JP17, JP18, JP19, JP20, JP21, JP22, JP23, JP24, JP25, JP26, JP27, JP28, JP29, JP30, JP31, JP32, JP33, JP34, JP35, JP36, JP37, JP38, JP39, JP40, JP41, JP42, JP43, JP44, JP45, JP46, JP47, JP48, JP49, JP62, JP63, JP64, JP65, JP66, JP67	J-JMPR-2PIN
27	Connector/SMA/Vertica l/TH			1	J1	SMA NO POP
28	Connector/BNC 75 ohm/5-pin/1.29 mm pitch/RA/TH	5413558-1	Tyco	2	J2, J4	BNC-5PIN
29	RJ45/no LED/1.27 mm pitch/8-pin/RA/TH	5621-1x1	Hesheng	1	J3	CONN_RJ48

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
30	Header/dual row/short/vertical/2.54 mm pin pitch	2x7		2	J5, J6	HEADER2X7
31	Header/single row/short/vertical/2.54 mm	1x6		1	J8	CON6
32	RJ45/no LED/1.27 mm pitch/8-pin/RA/TH	5621-1x1	Hesheng	4	J15, J18, J19, J21	RJ45x4_8
33	transformer/1:1/10/100 base-T/sop16-50-370	H1102	Pulse	4	J16, J17, J20, J22	H1102
34	Header/single row/short/vertical/2.54 mm pin pitch header	1x12		1	J25	CON12_0
35	IDC 10x2/100 mil-pitch/shrouded/vertical/TH	HL0705F	Foxconn	1	J26	IDC10X2
36	Header/dual row/short/vertical/2.54 mm pin pitch	2x10		1	J27	CON20A
37	TYPE B USB CONNECTOR	amp-787924	AMP	1	J29	USB_DEV
38	TYPE A DUAL USB CONNECTOR/RA/TH	tyco-5787617	Tyco	1	J30	USB_HOST_CON
39	Header/dual row/short/vertical/2.54 mm pin pitch	2x6		1	J31	JUMP2X6
40	Inductor/1 uH/2.76 A/20 %/3.9x3.9/	GSCD43-1R0	genericsz	1	L1	LPS4012-102NL
41	Inductor/2.2 uH/1.75 A/20 %/3.9x3.9	GSCD43-2R2	genericsz	2	L2, L3	LPS4012-222ML
42	Bead/3000 mA/75 ohm/0.025 ohm/SL1806	BLM41PG750 SN1L	Murata	21	L6, L7, L8, L9, L10, L11, L12, L13, L14, L15, L16, L17, L18, L19, L20, L21, L22, L23, L24, L25, L606	BLM41PG750SN1L
43				1	PD1	PADX2-80H60
44	Connector/D-sub9/male/RA/TH			4	P1, P2, P3, P8	CONNECTOR DB9 Male
45	Header/single row/short/vertical/2.54 mm pin pitch header	1x3		4	P4, P5, P6, P7	CON3

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
46	NPN Transistor/30 V/30 V/6 V/ 0.1 A/0.33 W/SOT23	BC848A	Infineon	1	Q4	BC848
47	Resistor Array/33Rohm/63 mW/ 5%/SR0603X4			8	RN1, RN2, RN3, RN4, RN5, RN6, RN7, RN8	33, 1%
48	Resistor/33Rohm/NO/1 %/SR0603/			101	R1, R3, R4, R5, R6, R8, R18, R19, R20, R21, R22, R23, R24, R25, R26, R27, R28, R29, R36, R37, R38, R39, R40, R41, R69, R70, R71, R74, R75, R76, R127, R128, R130, R134, R135, R136, R154, R157, R158, R159, R189, R192, R193, R194, R224, R227, R228, R229, R259, R262, R263, R264, R367, R368, R369, R372, R374, R389, R401, R500, R501, R502, R503, R504, R505, R506, R507, R508, R509, R510, R511, R512, R513, R514, R515, R516, R517, R518, R519, R520, R521, R522, R523, R524, R525, R526, R527, R529, R531, R532, R533, R534, R535, R600, R601, R627, R628, R630, R635, R636, R637	33-0603
49	Resistor/33Rohm/NO/1 %/SR0603			8	R2, R9, R370, R371, R373, R393, R402, R403	33-0603-NO POP

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
50	Resistor/4K7ohm/NO/1%/SR0603			47	R7, R77, R78, R79, R80, R82, R83, R84, R137, R141, R155, R161, R162, R163, R164, R165, R167, R172, R177, R190, R196, R197, R198, R199, R201, R202, R207, R210, R225, R231, R232, R233, R234, R236, R237, R242, R245, R260, R266, R267, R268, R269, R271, R272, R359, R404, R901	4.7K-0603
51	Resistor/75Rohm/NO/5%/SR0603			17	R10, R140, R143, R146, R147, R175, R176, R180, R181, R212, R213, R216, R217, R247, R248, R250, R251	75-0603
52	Resistor/0Rohm/NO/5%/SR0603			37	R11, R12, R13, R14, R110, R118, R138, R139, R142, R144, R145, R148, R149, R173, R174, R178, R179, R182, R183, R184, R208, R209, R211, R214, R215, R218, R219, R243, R244, R246, R249, R252, R253, R254, R332, R341, R405	0-0603
53	Resistor/61R9ohm/NO/1%/SR0603			2	R15, R16	61.9-0603
54	Resistor/51R1ohm/NO/1%/SR0603			1	R17	51.1-0603

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
55	Resistor/1Kohm/NO/1%/SR0603			75	R42, R44, R45, R46, R47, R48, R49, R50, R51, R52, R53, R54, R55, R56, R57, R58, R59, R60, R61, R62, R63, R64, R65, R66, R67, R68, R72, R124, R160, R169, R170, R171, R195, R204, R205, R206, R230, R239, R240, R241, R265, R274, R275, R276, R286, R287, R297, R298, R300, R302, R314, R315, R316, R317, R318, R319, R320, R325, R328, R331, R333, R334, R335, R338, R340, R343, R352, R353, R354, R355, R363, R364, R394, R399, R541	1K-0603
56	Resistor/1Kohm/NO/1%/SR0603			1	R43	1K-0603-NO POP
57	Resistor/330Rohm/NO/1%/SR0603			20	R73, R112, R124, R375, R376, R377, R378, R379, R380, R381, R382, R383, R384, R385, R386, R387, R388, R390, R391, R392	330-0603
58	Resistor/4K7ohm/NO/1%/SR0603			2	R81, R87	4.7K-0603-NO POP
59	Resistor/4R3ohm/NO/1%/SR0603			2	R103, R105	4.3-0603
60	Resistor/6 Kohm/NO/1%/SR0603			7	R106, R107, R108, R109, R116, R117, R119	68k-0603
61	Resistor/150Kohm/NO/5%/SR0603			2	R111, R122	150k-0603
62	Resistor/27Kohm/0.063W/1%			1	R113	27K-0603
63	Resistor/47Kohm/0.063W/5%			1	R114	47K-0603
64	Resistor/15Kohm/NO/5%/SR0603			1	R115	15K-0603

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manu- facturer	Qty	Reference	Part
65	Resistor/10Kohm/NO/5 %/SR0603			29	R120, R132, R133, R304, R306, R307, R308, R309, R310, R311, R312, R313, R321, R322, R323, R324, R326, R344, R345, R346, R347, R349, R350, R356, R357, R358, R540, R632, R633	10K-0603
66	Resistor/75Kohm/NO/1 %/SR0603			1	R121	75k-0603
67	Resistor/120Rohm/NO/ 5%/SR0603			6	R126, R129, R131, R626, R629, R631	120-0603
68	Resistor/49R9ohm/NO/ 1%/SR0603			16	R150, R151, R152, R153, R185, R186, R187, R188, R220, R221, R222, R223, R255, R256, R257, R258	49.9-0603
69	Resistor/6K49ohm/NO/ 1%/SR0603			4	R156, R191, R226, R261	6.49K-0603
70	Resistor/220Rohm/NO/ 1%/SR0603			8	R166, R168, R200, R203, R235, R238, R270, R273	220-0603
71	Resistor/121Kohm/NO/ 1%/SR0603			3	R277, R342, R400	121K-0603
72	Resistor/470Rohm/0.06 3W/5%			2	R280, R281	470-0603
73	Resistor/100Rohm/NO/ 1%/SR0603			11	R282, R283, R284, R285, R289, R290, R291, R292, R294, R295, R296	100-0603
74	Resistor/150Rohm/NO/ 5%/SR0603			5	R288, R299, R301, R303, R305	150-0603
75	Resistor/1Mohm/NO/1 %/SR0603			1	R293	1M-0603
76	Resistor/0Rohm/NO/5 %/SR0603			7	R327, R329, R330, R407, R408, R606, R900	0-0603-NO POP
77	Resistor/10Rohm/NO/5 %/SR0603			3	R336, R337, R339	10-0603
78	Resistor/100Kohm/NO/ 5%/SR0603			1	R348	100K-0603

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
79	Resistor/390Kohm/NO/1%/SR0603			1	R351	390K-0603
80	Resistor/43R2ohm/NO/1%/SR0603			1	R360	43.2-0603
81	Resistor/120Kohm/NO/1%/SR0603			1	R406	120k
82	Push button/4-pin/6x6 mm/RA/TH	TS6601V	Kingtek	1	SW1	PUSHBUTTON
83	Slide switch/8 ways/1.27 mm pitch/SMT	CHS-08TB1	COPAL	1	SW2	SW DIP-8
84	Slide switch/6 ways/1.27 mm pitch/SMT	CHS-06TB1	COPAL	1	SW3	SW DIP-6
85	Test terminal/1.02 mm hole/1-pin/TH	20-2137	VERO	11	TP1, TP2, TP3, TP4, TP5, TP6, TP7, TP16, TP17, TP19, TP20	TEST_POINT
86	Transformer/Dual ports/1CT:1:0.8/T1/sop 16-50-370	TX1099	PULSE	1	T1	TRANS TX1099
87	Clock driver/3.3V CMOS/1 input 10 output/QSOP20	PI49FCT3807BQE	Pericom	1	U1	PI49FCT3807BQE+AMX
88	Oscillator 125 MHz			1	U2	OSC-125MHz
89	CMOS switch/4 ways/QSOP16	QS3125QG	IDT	3	U3, U36, U37	IDTQS3125QG
90	NAND Flash/8 Gbit/8 bit/3.3 V/TSOP48/	NAND08GW3B2CN6	numonyx/ST	1	U4	NAND08GW3B2CN6
91	CMOS switch/10 ways/QSOP24	QS3861QG	IDT	1	U5	IDTQS3861QG
92	Transceiver/E1/CEPT/L QFP100	DS21354L	MAXIM	1	U6	DS21354
93	Flash/64 Mbit/16 bit/3.3 V/boot block/TSOP48/	M28W640HCT70N6E	numonyx	2	U7, U10	M28W640HCT
94	D-type latch/16 bit/TSSOP48	74LCX16373TTR	ST	2	U8, U9	74LCX16373TTR
95	Reset IC/3V/SOT143-4/RoHs	STM811SW16F	ST	1	U11	STM811
96	Buffer/8 bit/TSSOP20	74LCX244TTR	ST	1	U12	74LCX244TTR
97	Switching Power/2.7 V-5.5 V/1.5 V-1.8 V/3.9 A-6.1 A/ QFPN48 7x7	PM6641	ST	1	U13	PM6641

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
98	LDO/15 Vmax/2.5 V/1 A/2%/SOT223	LD1117AS25 TR	ST	1	U15	LD1117A
99	Transceiver/RS-485/SO8	ST485CDR	ST	2	U16, U60	ST485C
100	Oscillator 8.192 MHz			1	U17	OSC 8.192MHz
101	Transceiver/100Base-TX PHY/TQFP48	KSZ8041TL	Micrel	4	U18, U19, U20, U21	KSZ8041TL/KSZ8041FTL
102	SPEAr310 LFBGA289	SPEAr310	ST	1	U22	SPEAr310
103	DDR2/1 Gbit/BGA84	MT47H64M16 HR3	Micron	1	U23	MT47H64M16HR
104	Transceiver/100Base-TX PHY/TQFP64	STE100P	ST	1	U24	STE100P_0
105	Connector/RJ45	HR911105A	Hanrun	1	U25	HR911105A
106	Flash/64 Mbit/8 bit/SPI/3.3 V/	M25P64-VMF6PT	ST	1	U26	M25P64
107	Battery holder/3 V/220 mAh/battery-holder-cr2032	CR2032-2-1	Keyu	1	U27	BATT BR2032
108	EEPROM/4 Kbit/8 bit/I2C	M24C04-WMN6TP	ST	1	U28	M24C04
109	Flash/4 Mbit/8 bit/SPI/3.3 V	M25P40-VMN6T	ST	1	U29	M25P40
110	Power MOSFET	ST2052BDR	ST	1	U31	ST2052
	Transceiver/RS-232/SO16	ST3232CDR	ST	3	U32, U33, U34	ST3232CDC
112	Oscillator 2.048 MHz/			1	U35	OSC 2.048MHz
113	CPLD/10 ns/72 user I/Os/TQFP100/	XC9572XL-10TQ100C	Xilinx	1	U38	XC9572XL
114	Inverter/1.65 5.5 V	74LVC1G14GW	NXP	2	U40, U41	74LVC1G14
115	Overvoltage protection	STBP120BVD K6F	ST	1	U61	ST STBP120C
116	3-pin power jack diameter 2.1 mm			1	VB1	PWS-JACK
117	Crystal/25 MHz/NO/1HC49			1	Y1	25MHZ
118	Crystal/32.768 kHz/			1	Y2	32.768KHZ
119	Crystal/24MHz/NO/HC49			1	Y3	24MHZ

Table 32. SPEAr310 bill of materials (BOM) (continued)

Item	Description	Part number	Manufacturer	Qty	Reference	Part
120	Zener Diode/5.6 V/0.5 A/0.5 W	MMSZ5232BT1	Onsemi	1	Z1	MMSZ5232BT1
121	Bat/3V/220 mAh/CR2032	CR2032	TMMQ	1		
122	LED/RED/SLED0805			2	D2, D3	RED-NO POP
123	Resistor/680Rohm/NO/1%/	SZDZ6201CR0603F680R	ROYALOH M	16	R73, R112, R375, R376, R377, R378, R379, R380, R381, R382, R383, R384, R385, R386, R387, R388	680-0603
124	Resistor/330Rohm/NO/1%/			2	R390, R391	330-0603-NO POP

Appendix A Licence agreements

DEMO PRODUCT LICENSE AGREEMENT

By using this Demonstration Product, You are agreeing to be bound by the terms and conditions of this agreement. Do not use this Demonstration Product until You have read and agreed to the following terms and conditions. The use of the Demonstration Product implies automatically the acceptance of the following terms and conditions.

LICENSE. STMicroelectronics ("ST") grants You the right to use the enclosed demonstration board offering limited features only to evaluate and test ST products, including any incorporated and/or accompanying demo software, components and documentation identified with the order code "EVALSPEAR310" (collectively, the "Demo Product") solely only for your evaluation and testing purposes. The Demo Product shall not be, in any case, directly or indirectly assembled as a part in any production of Yours as it is solely developed to serve demonstration purposes and has no direct function and is not a finished product. Certain demo software included with the Demo Product may be covered under a separate accompanying end user license agreement, in which case the terms and conditions of such end user license agreement shall apply to that demonstration software.

DEMO PRODUCT STATUS. The Demo Product is offering limited features allowing You only to evaluate and test the ST products. You are not authorized to use the Demo Product in any production system, and may not be offered for sale or lease, or sold, leased or otherwise distributed. If the Demo Product is incorporated in a demonstration system, the demonstration system may be used by You solely for your evaluation and testing purposes. Such demonstration system may not be offered for sale or lease or sold, leased or otherwise distributed and must be accompanied by a conspicuous notice as follows: "This device is not, and may not be, offered for sale or lease, or sold or leased or otherwise distributed".

OWNERSHIP AND COPYRIGHT. Title to the Demo Product, demo software, related documentation and all copies thereof remain with ST and/or its licensors. You may not remove the copyrights notices from the Demo Product. You may make one (1) copy of the software for back-up or archival purposes provided that You reproduce and apply to such copy any copyright or other proprietary rights notices included on or embedded in the demonstration software. You agree to prevent any unauthorized copying of the Demo Product, demonstration software and related documentation.

RESTRICTIONS. You may not sell, assign, sublicense, lease, rent or otherwise distribute the Demo Product for commercial purposes (unless you are an authorized ST distributor provided that all the other clauses of this DEMO

PRODUCT LICENSE AGREEMENT shall apply entirely), in whole or in part, or use Demo Product in production system. Except as provided in this Agreement or in the Demo Product's documentation, You may not reproduce the demonstration software or related documentation, or modify, reverse engineer, de-compile or disassemble the demonstration software, in whole or in part.

You warrant to ST that the Demo Product will be used and managed solely and exclusively in a laboratory by skilled professional employees of Yours with proven expertise in the use and management of such products and that the Demo Product shall be used and managed according to the terms and conditions set forth in the related documentation provided with the Demo Product.

According to European Semiconductor Industry Association (ESIA) letter, "ESIA Response on WEEE Review (May 2008) of the Directive 2002/96/EC on Waste Electrical and Electronic Equipment (WEEE)"; Semiconductor products and evaluation & demonstration boards are not in the scope of the Directive 2002/96/EC of the European Parliament and of the Council on waste electrical and electronic equipment (WEEE). Consequently aforementioned products do not have to be registered nor are they subject to the subsequent obligations.

NO WARRANTY. The Demo Product is provided "as is" and "with all faults" without warranty of any kind expressed or implied. ST and its licensors expressly disclaim all warranties, expressed, implied or otherwise, including without limitation, warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights. ST does not warrant that the use in whole or in part of the Demo Product will be interrupted or error free, will meet your requirements, or will operate with the combination of hardware and software selected by You. You are responsible for determining whether the Demo Product will be suitable for your intended use or application or will achieve your intended results.

ST shall not have any liability in case of damages, losses, claims or actions anyhow caused from combination of the Demo Product with another product, board, software or device.

ST has not authorized anyone to make any representation or warranty for the Demo Product, and any technical, applications or design information or advice, quality characterization, reliability data or other services provided by ST shall not constitute any representation or warranty by ST or alter this disclaimer or warranty, and in no additional obligations or liabilities shall arise from ST's providing such information or services. ST does not assume or authorize any other person to assume for it any other liability in connection with its Demo Products.

All other warranties, conditions or other terms implied by law are excluded to the fullest extent permitted by law.

LIMITATION OF LIABILITIES. In no event ST or its licensors shall be liable to You or any third party for any indirect, special, consequential, incidental, punitive damages or other damages (including but not limited to, the cost of labour, re-qualification, delay, loss of profits, loss of revenues, loss of data, costs of procurement of substitute goods or services or the

like) whether based on contract, tort, or any other legal theory, relating to or in connection with the Demo Product, the documentation or this Agreement, even if ST has been advised of the possibility of such damages. In no event shall ST's aggregate liability to You or any third party under this agreement for any cause action, whether based on contract, tort, or any other legal theory, relating to or in connection with the Demo Product, the documentation or this agreement shall exceed the purchase price paid for the Demo Product if any.

TERMINATION. ST may terminate this license at any time if You are in breach of any of its terms and conditions. Upon termination, You will immediately destroy or return all copies of the demo software and documentation to ST.

APPLICABLE LAW AND JURISDICTION. In case of dispute and in the absence of an amicable settlement, the only competent jurisdiction shall be the Courts of Geneva, Switzerland. The applicable law shall be the law of Switzerland. The UN Convention on contracts for the International Sales of Goods shall not apply to these General Terms and Conditions of Sale.

SEVERABILITY. If any provision of this agreement is or becomes, at any time or for any reason, unenforceable or invalid, no other provision of this agreement shall be affected thereby, and the remaining provisions of this agreement shall continue with the same force and effect as if such unenforceable or invalid provisions had not been inserted in this Agreement.

WAIVER. The waiver by either party of any breach of any provisions of this Agreement shall not operate or be construed as a waiver of any other or a subsequent breach of the same or a different provision.

RELATIONSHIP OF THE PARTIES. Nothing in this Agreement shall create, or be deemed to create, a partnership or the relationship of principal and agent or employer and employee between the Parties. Neither Party has the authority or power to bind, to contract in the name of or to create a liability for the other in any way or for any purpose.

RECYCLING. The Demo Product is not to be disposed as an urban waste. At the end of its life cycle, differentiated waste collection must be followed, as stated in the directive 2002/96/EC.

In all the countries belonging to the European Union (EU Dir. 2002/96/EC) and those following differentiated recycling, the Demo Product is subject to differentiated recycling at the end of its life cycle, therefore:

It is forbidden to dispose the Demo Product as an undifferentiated waste or with other domestic wastes. Consult the local authorities for more information on the proper disposal channels.

It is mandatory to sort the demo product and deliver it to the appropriate collection centers, or, when possible, return the demo product to the seller.

An incorrect Demo Product disposal may cause damage to the environment and is punished by the law.

SOFTWARE LICENSE AGREEMENT

This Software License Agreement ("Agreement") is displayed for You to read prior to downloading and using the Licensed Software. If you choose not to agree with these provisions, do not download or install the enclosed Licensed Software and the related documentation and design tools. By using the Licensed Software, You are agreeing to be bound by the terms and conditions of this Agreement. Do not use the Licensed Software until You have read and agreed to the following terms and conditions. The use of the Licensed Software implies automatically the acceptance of the following terms and conditions.

DEFINITIONS

Licensed Software: means the enclosed demonstration software and all the related documentation and design tools licensed in the form of object and/or source code as the case maybe.

Product: means a product or a system that includes or incorporates solely and exclusively an executable version of the Licensed Software and provided further that such Licensed

Software executes solely and exclusively on ST products.

LICENSE

STMicroelectronics ("ST") grants You a non-exclusive, worldwide, non-transferable (whether by assignment, law, sublicense or otherwise), revocable, royalty-free limited license to:

(i) make copies, prepare derivatives works, display internally and use internally the source code version of the Licensed Software for the sole and exclusive purpose of developing executable versions of such Licensed Software only for use with the Product;

(ii) make copies, prepare derivatives works, display internally and use internally object code versions of the Licensed Software for the sole purpose of designing, developing and manufacturing the Products;

(iii) make, use, sell, offer to sell, import or otherwise distribute Products.

OWNERSHIP AND COPYRIGHT

Title to the Licensed Software, related documentation and all copies thereof remain with ST and/or its licensors. You may not remove the copyrights notices from the Licensed Software.

You may make one (1) copy of the Licensed Software for back-up or archival purposes provided that You reproduce and apply to such copy any copyright or other proprietary rights notices included on or embedded in the Licensed Software. You agree to prevent any unauthorized copying of the Licensed Software and related documentation.

RESTRICTIONS

Unless otherwise explicitly stated in this Agreement, You may not sell, assign, sublicense, lease, rent or otherwise distribute the Licensed for commercial purposes, in whole or in part purposes (unless you are an authorized ST distributor provided that all the other clauses of this DEMO PRODUCT LICENSE AGREEMENT shall apply entirely).

You acknowledge and agree that any use, adaptation translation or transcription of the

Licensed Software or any portion or derivative thereof, for use with processors manufactured by or for an entity other than ST is a material breach of this Agreement and requires a separate license from ST. No source code and/or object code relating to and/or based upon Licensed Software is to be made available by You to any third party for whatever reason.

You acknowledge and agrees that the protection of the source code of the Licensed Software warrants the imposition of security precautions and You agree to implement reasonable security measures to protect ST's proprietary rights in the source code of the Licensed Software. You shall not under any circumstances copy, duplicate or otherwise reproduce the source code of the Licensed Software in any manner, except as reasonably necessary to exercise Your rights hereunder and make one back-up copy. You are granted the right to make one archival or backup copy of the source code of the Licensed Software, which copy shall be marked as an archival copy and as the confidential information of ST. Access to the source code of the Licensed Software shall be restricted to only those of Your employees with a need-to-know for the purpose of this Agreement.

You will not under any circumstances permit the source code of the Licensed Software in any form or medium (including, but not limited to, hard copy or computer print-out) to be removed from your official premises as you have informed us. The source code of the Licensed Software must remain inside your official premises, as you have informed us. You will lock the source code of the Licensed Software and all copies thereof in a secured storage inside your official premises at all times when the source code of the Licensed Software is not being used as permitted under this Agreement.

You will inform all Your employees who are given access to the source code of the Licensed Software of the foregoing requirements, and You will take all reasonable precautions to ensure and monitor their compliance with such requirements. You agree to promptly notify ST in the event of a violation of any of the foregoing, and to cooperate with ST to take any remedial action appropriate to address the violation. You shall keep accurate records with respect to its use of the source code of the Licensed Software. In the event ST demonstrates to You a reasonable belief that the source code of the Licensed Software has been used or distributed in violation of this Agreement, ST may by written notification request certification as to whether such unauthorized use or distribution has occurred. You shall reasonably cooperate and assist ST in its determination of whether there has been unauthorized use or distribution of the source code of the Licensed Software and will take appropriate steps to remedy any unauthorized use or distribution.

You agree that ST shall have the right (where ST reasonably suspects that the terms and conditions of this Agreement with reference to Restriction clause have not been complied with) upon reasonable notice to enter Your official premises in order to verify your compliance with this Restriction clause.

NO WARRANTY

The Licensed Software is provided "as is" and "with all faults" without warranty of any kind expressed or implied. ST and its licensors expressly disclaim all warranties, expressed, implied or otherwise, including without limitation, warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights. ST does not warrant that the use in whole or in part of the Licensed Software will be interrupted or error free, will meet your requirements, or will operate with the combination of hardware and software selected by You.

You are responsible for determining whether the Licensed Software will be suitable for your intended use or application or will achieve your intended results. ST has not authorized anyone to make any representation or warranty for the Licensed Software, and any technical, applications or design information or advice, quality characterization, reliability data or other services provided by ST shall not constitute any representation or warranty by ST or alter this disclaimer or warranty, and in no additional obligations or liabilities shall arise from ST's providing such information or services. ST does not assume or authorize any other person to assume for it any other liability in connection with its Licensed Software.

Nothing contained in this Agreement will be construed as:

- (i) a warranty or representation by ST to maintain production of any ST device or other hardware or software with which the Licensed Software may be used or to otherwise maintain or support the Licensed Software in any manner; and
- (ii) a commitment from ST and/or its licensors to bring or prosecute actions or suits against

third parties for infringement of any of the rights licensed hereby, or conferring any rights to bring or prosecute actions or suits against third parties for infringement. However, ST has the right to terminate this Agreement immediately upon receiving notice of any claim, suit or proceeding that alleges that the Licensed Software or your use or distribution of the Licensed

Software infringes any third party intellectual property rights.

All other warranties, conditions or other terms implied by law are excluded to the fullest extent permitted by law.

LIMITATION OF LIABILITIES

In no event ST or its licensors shall be liable to You or any third party for any indirect, special, consequential, incidental, punitive damages or other damages (including but not limited to, the cost of labour, re-qualification, delay, loss of profits, loss of revenues, loss of data, costs of procurement of substitute goods or services or the like) whether based on contract, tort, or any other legal theory, relating to or in connection with the Licensed Software, the documentation or this Agreement, even if ST has been advised of the possibility of such damages.

In no event shall ST's liability to You or any third party under this Agreement, including any claim with respect to any third party intellectual property rights, for any cause of action exceed

100 US\$. This section does not apply to the extent prohibited by law. For the purposes of this section, any liability of ST shall be treated in the aggregate.

TERMINATION

ST may terminate this license at any time if You are in breach of any of its terms and conditions. Upon termination, You will immediately destroy or return all copies of the software and documentation to ST.

APPLICABLE LAW AND JURISDICTION

In case of dispute and in the absence of an amicable settlement, the only competent jurisdiction shall be the Courts of Geneva, Switzerland. The applicable law shall be the law of Switzerland.

SEVERABILITY

If any provision of this agreement is or becomes, at any time or for any reason, unenforceable or invalid, no other provision of this agreement shall be affected thereby, and the remaining provisions of this agreement shall continue with the same force and effect as if such unenforceable or invalid provisions had not been inserted in this Agreement.

WAIVER

The waiver by either party of any breach of any provisions of this Agreement shall not operate or be construed as a waiver of any other or a subsequent breach of the same or a different provision.

RELATIONSHIP OF THE PARTIES

Nothing in this Agreement shall create, or be deemed to create, a partnership or the relationship of principal and agent or employer and employee between the Parties. Neither Party has the authority or power to bind, to contract in the name of or to create a liability for the other in any way or for any purpose.

Revision history

Table 33. Document revision history

Date	Revision	Changes
27-Oct-2009	1	Initial release.
25-Feb-2010	2	Changed the title of the document. Minor text changes.

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2010 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com